FLXible Neon 2 Super Slim Flexible LED With Spot-free Output

Curve perfection with FLXible Neon

c 🕕 us listed 🗲 🕼 🗵

- Bend direction Vertically
- Ultra Slim spot free illumination
- Dimmable with 0-10V, Forward/Reverse Phase
- Indoor and Outdoor Application
- Field Cuttable (38.5mm) for customized length
- Available in Standard Lengths of 1, 2, 3, 4, 5M reels






Specification


Model Number	Power Input	Lamp Power	Luminous Flux	Efficiency	Available Color	Color Rendering	Operating Temperature
FN2 40K-24V-1M	DC24V	12.5W/M	650 lm	65 lm/W	2,200K/2,400K/3,000K/3,500K/4,000K/5,000K/6,000K	Ra > 80	−10°C to 50°C
FN2 40K-24V-2M	DC24V	12.5W/M	1,300 lm	65 lm/W	2,200K/2,400K/3,000K/3,500K/4,000K/5,000K/6,000K	Ra > 80	−10°C to 50°C
FN2 40K-24V-3M	DC24V	12.5W/M	1,950 lm	65 lm/W	2,200K/2,400K/3,000K/3,500K/4,000K/5,000K/6,000K	Ra > 80	−10°C to 50°C
FN2 40K-24V-4M	DC24V	12.5W/M	2,600 lm	65 lm/W	2,200K/2,400K/3,000K/3,500K/4,000K/5,000K/6,000K	Ra > 80	−10°C to 50°C
FN2 40K-24V-5M	DC24V	12.5W/M	3,250 lm	65 lm/W	2,200K/2,400K/3,000K/3,500K/4,000K/5,000K/6,000K	Ra > 80	−10°C to 50°C


* Ip Rate


IP67 with Factory Termination (Customized Length Available) IP65 with Field Termination IP20 with Indoor Termination

Powerfeed type











116

П
\Box
7
m
9
10


* Bracket & Screw are included every 25cm

Dimension





Bottom feed



FLXible Neon can be cut every 38.5mm. Please follow the cutting point mark to cut precisely as needed.

	aight Feed (Customized Length Available)
FN2 40K-24V (5m) FN2 40K-24V (4m) FN2 40K-24V (3m)	FN2 40K-24V (2m) FN2 40K-24V (1m)
ⓑ FLXible Neon 2 Lef	t Side Feed (Customized Length Available
FN2 40K-24V-LS (5r FN2 40K-24V-LS (4r FN2 40K-24V-LS (3r	m) FN2 40K-24V-LS (2m) m) FN2 40K-24V-LS (1m)
© FLXible Neon 2 Bot	ttom Feed (Customized Length Available)
FN2 40K-24V-BS (5r FN2 40K-24V-BS (4r FN2 40K-24V-BS (3r	m) FN2 40K-24V-BS (1m)
Mounting Brackets	;
FN2-BRACKET1, 1se	t = 4pcs
FN2 Extrusion Line	(1,200mm)
FN2-EXL	
(f) Transparent Braket	
FN2 - BRACKETS1-T	
9 Expanding Stick	
FN-EPS	
h Indoor Power Cable FN2-INPC (2,500mm) with END CAP
 Indoor Power Cable FN2-INPC (2,500mm Indoor Power Cable 	e Bottom Feed (Max.62.5W)
h Indoor Power Cable FN2-INPC (2,500mm	e Bottom Feed (Max.62.5W)
 Indoor Power Cable FN2-INPC (2,500mm Indoor Power Cable FN2-INPC-BS (2,500 	e Bottom Feed (Max.62.5W)
 Indoor Power Cable FN2-INPC (2,500mm Indoor Power Cable FN2-INPC-BS (2,500 	e Bottom Feed (Max.62.5W)
 Indoor Power Cable FN2-INPC (2,500mm Indoor Power Cable FN2-INPC-BS (2,500 Indoor Direct Conn FN2-INCPL 	e Bottom Feed (Max.62.5W) Omm) with END CAP ector
 Indoor Power Cable FN2-INPC (2,500mm Indoor Power Cable FN2-INPC-BS (2,500 Indoor Direct Conn FN2-INCPL 	e Bottom Feed (Max.62.5W) Dmm) with END CAP ector Cable
 Indoor Power Cable FN2-INPC (2,500mm Indoor Power Cable FN2-INPC-BS (2,500 Indoor Direct Conn FN2-INCPL Indoor Connecting 	e Bottom Feed (Max.62.5W) e Bottom Feed (Max.62.5W) Dmm) with END CAP ector Cable PN2-INPTC4 (1,200mm) n) FN2-INPTC6 (1,800mm)
 Indoor Power Cable FN2-INPC (2,500mm Indoor Power Cable FN2-INPC-BS (2,500 Indoor Direct Conn FN2-INPC-BS (2,500 Indoor Direct Conn FN2-INPC Indoor Connecting FN2-INPTC (150mm) FN2-INPTC1 (300mn FN2-INPTC2 (600mn 	e Bottom Feed (Max.62.5W) e Bottom Feed (Max.62.5W) Dmm) with END CAP ector Cable PN2-INPTC4 (1,200mm) n) FN2-INPTC6 (1,800mm)
 Indoor Power Cable FN2-INPC (2,500mm Indoor Power Cable FN2-INPC-BS (2,500 Indoor Direct Conn FN2-INPC-BS (2,500 Indoor Direct Conn FN2-INPC Indoor Connecting FN2-INPTC (150mm) FN2-INPTC1 (300mn FN2-INPTC2 (600mn 	e Bottom Feed (Max.62.5W) e Bottom Feed (Max.62.5W) Dmm) with END CAP ector Cable PN2-INPTC4 (1,200mm) n) FN2-INPTC6 (1,800mm)
 Indoor Power Cable FN2-INPC (2,500mm) Indoor Power Cable FN2-INPC-BS (2,500) Indoor Direct Conn FN2-INCPL Indoor Connecting FN2-INCPL Indoor Connecting FN2-INPTC (150mm) FN2-INPTC1 (300mn FN2-INPTC2 (600mn) Field Termination FN2-FTKIT 	e Bottom Feed (Max.62.5W) mm) with END CAP ector Cable n) FN2-INPTC4 (1,200mm) n) FN2-INPTC6 (1,800mm) n)
 Indoor Power Cable FN2-INPC (2,500mm Indoor Power Cable FN2-INPC-BS (2,500 Indoor Direct Conn FN2-INPC-BS (2,500 Indoor Connecting FN2-INPTC (150mm) FN2-INPTC (150mm) FN2-INPTC1 (300mm FN2-INPTC2 (600mm Field Termination FN2-FTKIT LED Driver with 12w 	e Bottom Feed (Max.62.5W) e Bottom Feed (Max.62.5W) Dmm) with END CAP ector Cable 0 FN2-INPTC4 (1,200mm) n) FN2-INPTC6 (1,800mm) n) vay distributor, with power cord (1,800mm)
 Indoor Power Cable FN2-INPC (2,500mm) Indoor Power Cable FN2-INPC-BS (2,500) Indoor Direct Conn FN2-INCPL Indoor Connecting FN2-INCPL Indoor Connecting FN2-INPTC (150mm) FN2-INPTC1 (300mn FN2-INPTC2 (600mn) Field Termination FN2-FTKIT 	e Bottom Feed (Max.62.5W) mm) with END CAP ector Cable n) FN2-INPTC4 (1,200mm) n) FN2-INPTC6 (1,800mm) n)
 Indoor Power Cable FN2-INPC (2,500mm) Indoor Power Cable FN2-INPC-BS (2,500) Indoor Direct Conn FN2-INCPL Indoor Connecting FN2-INPTC (150mm) FN2-INPTC (150mm) FN2-INPTC (600mn) Field Termination FN2-FTKIT IED Driver with 12w Part No Capacity 	with END CAP e Bottom Feed (Max.62.5W) Dmm) with END CAP ector Cable Physical Product (1,200mm) n) FN2-INPTC4 (1,200mm) n) FN2-INPTC6 (1,800mm) n) FLC30-24V/T FLC30-24V/T 30W 24V
 Indoor Power Cable FN2-INPC (2,500mm) Indoor Power Cable FN2-INPC-BS (2,500) Indoor Direct Conn FN2-INCPL Indoor Connecting FN2-INCPL Indoor Connecting FN2-INPTC (150mm) FN2-INPTC1 (300mm FN2-INPTC2 (600mm) Field Termination FN2-FTKIT IED Driver with 12w Part No Capacity LED Driver : FLC200 	with END CAP e Bottom Feed (Max.62.5W) Dmm) with END CAP ector Cable 0 FN2-INPTC4 (1,200mm) n) FN2-INPTC6 (1,800mm) n) FN2-INPTC6 (1,800mm) n) FLC30-24V/T FLC30-24V/T FLC75-24V-P/T 30W 24V 75W 24V -24V/T (200W, DC24V)
 Indoor Power Cable FN2-INPC (2,500mm) Indoor Power Cable FN2-INPC-BS (2,500) Indoor Direct Conn FN2-INCPL Indoor Connecting FN2-INPTC (150mm) FN2-INPTC (150mm) FN2-INPTC (600mn) Field Termination FN2-FTKIT IED Driver with 12w Part No Capacity 	with END CAP e Bottom Feed (Max.62.5W) Dmm) with END CAP ector Cable P P

FDA-L2M0 : Max. 200W (100W/CH, 2CH) FDA-L5M : Max. 200W (50W/CH, 5CH)

④ Dimming Interface (Dail): FDD-L1DA

Max. 200W (100W/fed, 2feeds)

FLXible Neon 2

